PALS 9K | Tags

60011-E | Personal Mobile **Transmitter**

60011-E - Personal Mobile **Transmitter**

The 60011 Personal Mobile Transmitter (PMT) offers the highest standard in state of the art radio frequency signaling, utilizing a combination of 900 MHz direct sequence spread spectrum frequency technology. The PMT provides different alarming options and will provide location data in an alarm situation when used in conjunction with other Actall's IRT Locators, Wireless RF Locators and the Crisis Controller® Windows® based software. All PMT's are fully supervised for any malfunction, tamper or low battery condition. PMT's are used in conjunction with Actall's Personal Alarm Locating System (PALS®).



Features & Benefits

- Compatible with the PALS® system components
- Panic Button, Emergency Pull Cord and Person Down alarms are standard
- Long range transmissions with the use of wireless repeaters for full site coverage
- Guard Tour options are available
- Rugged 1 piece design using high impact Lexan® plastic
- **Extended battery life** (up to 9 months depending on features and usage)
- Full transmitter supervision includes alarms for low battery, tamper and inactivity
- TR indoor and RF outdoor locating capabilities
- Exclusive Actall 60110 IR Lapel Reader can be used when inadvertently covered by clothing
- Heavy duty nylon holsters available

Specifications

DIMENSIONS

Height 3.75" Width 1.75" Depth .875"

Polycarbonate/ABS plastic/Lexan®

WEIGHT

Approximately 4 ounces

OPERATING TEMPERATURE

0° to 50° Centigrade

BATTERY TYPE

3 V Lithium Battery, Duracell 123A/Panasonic (or approved equivalent)

*Battery Life when deployed will vary as a function of duty time used, frequency of alarm transmissions sent, LED brightness/frequency, location broadcast interval settings and environmental conditions at your site. Based upon 240mAh CR 2032 (Energizer). Ask your Actall Sales Representative for more details.















